

ZENER	ZENER	TENSÃO VOLTS	POTÊNCIA WATTS
1N746A	BZX79C3V3	3,3	0,5
1N747A	BZX79C3V6	3,6	0,5
1N748A	BZX79C3V9	3,9	0,5
1N750A	BZX79C4V7	4,7	0,5
1N751A	BZX79C5V1	5,1	0,5
1N752A	BZX79C5V6	5,6	0,5
1N753A	BZX79C6V2	6,2	0,5
1N754A	BZX79C6V8	6,8	0,5
1N755A	BZX79C7V5	7,5	0,5
1N756A	BZX79C8V2	8,2	0,5
1N757A	BZXT9C9V1	9,1	0,5
1N758A	BZX79C10	10	0,5
1N962B	BZX79C11	11	0,5
1N759A	BZXT9C12	12	0,5
1N964B	BZX79C13	13	0,5
1N965B	BZX79C15	15	0,5
1N966B	BZX79C16	16	0,5
1N967B	BZX79C18	18	0,5
1N968B	BZX79C20	20	0,5
1N969B	BZX79C22	22	0,5
1N970B	BZX79C24	24	0,5
1N971B	BZX79C27	27	0,5
1N972B	BZX79C30	30	0,5
1N973B	BZX79C33	33	0,5
1N4728A	BZX81C3V3	3,3	1
1N4729A	BZX81C3V6	3,6	1
1N4730A	BZX81C3V9	3,9	1
1N4731A	BZX81C4V3	4,3	1
1N4732A	BZX81C4V7	4,7	1
1N4733A	BZX81C5V1	5,1	1
1N4734A	BZX81C5V6	5,6	1
1N4735A	BZX81C6V2	6,2	1
1N4736A	BZX81C6V8	6,8	1
1N4737A	BZX81C7V5	7,5	1
1N4738A	BZX81C8V2	8,2	1
1N4739A	BZX81C9V1	9,1	1
1N4740A	BZX81C10	10	1
1N4741A	BZX81C11	11	1
1N4742A	BZX81C12	12	1
1N4743A	BZX81C13	13	1
1N4744A	BZX81C15	15	1
1N4745A	BZX81C16	16	1
1N4746A	BZX81C18	18	1
1N4747A	BZX81C20	20	1
1N4748A	BZX81C22	22	1
1N4749A	BZX81C24	24	1
1N4750A	BZX81C27	27	1
1N4751A	BZX81C30	30	1
1N4752A	BZX81C33	33	1